





EYEHOMELIFE EYEHOME

EYEHOMELIFECO

Stand alone smoke and CO detectors for home use

The EYEHOMELife and EYEHOME detector is a photodetector that uses one of the most advanced optical detection cameras. It is designed to provide home fire protection without wiring and is easy to install.

The detector's red indicator light is easily visible. It flashes once every minute to indicate that the detector is in a surveillance state. When a fire alarm occurs, the indicator light will remain on continuously, the buzzer will sound for a long period of time and the alarm information will be sent via Wi-fi to the cloud (EYEHOMELife), and from here to the APP until it is deactivated.

The EYEHOMELifeCO gas detector is designed to provide protection in open areas without wiring, and is easy to install and mount.

The design and colour make it ideal for use in the home and small commercial premises. It is designed to detect carbon monoxide

FEATURES

EYEHOMELIFE

- Surface mounted
- Sound warning
- LED indicator
- Wireless connection (easy to install)
- Automatic low battery warning
- Compatible with the latest versions of EN-14604 standards
- Wi-Fi connection (EYEHOMELife)

EYEHOMELIFECO

- Detects carbon monoxide.
- Easy to install, mounting bracket included.
- LCD display.
- 85 dB audible alarm and LED warning light.
- Low battery detection.
- High quality, durable sensor.
- Self-diagnosis function by intelligent MCU software.
- Excellent reliability and high stability.
- Ideal for all kitchens.
- EN50291-1:2018 approval (TUV Certificate ID:1111252250).

TECHNICAL FEATURES	EYEHOMELIFE	EYEHOME
Power supply	9VDC (wit battery 6F22/6LR1)	9VDC (with battery 6F22)
Operating current	standby ≤ 8µA/alarm ≤ 400mA	standby ≤ 8µA/alarm ≤ 20mA
Operating temperature	-10°C ~ 55°C	
Humidity	≤ 95% HR (without condensation)	
Wi-fi	2.4GHZ	Sin Wi-fi
Sensibility	0.18 at 0.26dBM	
Sound level	≥ 85dB @ 3m and ≥ 93dB @ 1m	
Material	white ABS	
Dimensions	Ø105 x 43mm	
Weight	130g	
Standard	EN 14604:2005+2005/AC:2008	

EYEHOMELIFECO TECHNICAL FEATURES			
Operating voltage	3VDC		
Operating current	standby <15µA		
Operating corrent	alarm ≤ 40mA		
Operating temperature	-10°C ~ 40°C		
Alarm	85dB a 3m		
Humidity	≤ 95% RH		
Dimensions	104x104x39,2mm		



Compositor Wagner, 8

P.J Can Jardí 08191 Rubí

Barcelona (+34) 935 862 690 cofem@cofem.com www.cofem.com